

model 9001EXPC1D1

Emergency Alarm System

FEATURES & BENEFITS

AUDIBLE/VISUAL

Notification of an emergency is clearly noticeable with a brightly flashing red light and easily recognizable with a 90 db buzzer.

FLOW SWITCH

The alarm is activated by an 1-1/4" IPS double pole, double throw brass flow switch that is supplied with an extra set of electrical contacts for remote alarm hook-up.

FLEXIBILITY

The alarm is easily placed in a number of mounting configurations with the supplied pipe clamp.

OPTIONS

For more information, visit www.hawsco.com or call (888) 640-4297




SPECIFICATIONS


Model 9001EXPC1D1 emergency alarm and light system will be operated by a double pole, double throw flow switch, which contains multiple sets of contacts for remote activation, and activates an red flashing light and buzzer at 90 db, audible at 10 feet (304.8 cm). Switch will activate at 2.4 gpm (9.08 L). System can be mounted to pipe or wall. Voltage: 120 VAC, 50 or 60 cycles, Class 1 Div 1, Group C & D. Supply: 1-1/4" IPS. Model 9001EXPC1D1 is CSA electrical certified, TYPE 4 (Nema 4 equivalent). Temperature code T4

APPLICATIONS

Specifically, this alarm can be used with almost any Haws combination shower/eyewash model. Entire unit is CSA electrical certified, TYPE 4. (Nema 4 equivalent)







ELECTRICAL WIRING DIAGRAM



NOTES: (CONTINUED FROM SHEET 1)

- 6 LIGHT REPLACEMENT INSTRUCTIONS:
 - 1) REMOVE GUARD/GLOBE ASSEMBLY:
 FIRST LOOSEN SET SCREW (LOCATED ON GUARD WHERE SHOWN). NEXT, ROTATE ASSEMBLY COUNTER CLOCKWISE UNTIL GUARD IS FREE FROM PENDANT MOUNT AND LAMP IS EXPOSED.
 - 2) ONLY REPLACE LAMP WITH HAWS P/N 0003225505.

 WARNING EXPLOSION HAZARD SUBSTITUTION OF

 COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS 1,

 DIVISION 1.
 - 3) REPLACE GUARD/GLOBE ASSEMBLY:
 ROTATE ASSEMBLY CLOCKWISE ONTO THE PENDANT MOUNT
 UNTIL TIGHT AND TIGHTEN SET SCREW.

